

3/17/17

1

Description

A communications network, in particular for telephony

Technical Field

The present invention relates to a communications network, in particular for telephony.

5 Background Art

As is known, at present in the communications systems for cellular telephony the mobile terminals (cellular phones) dialog by means of radio frequencies with the Base Station Systems, hereinafter referred to with the abbreviation BSS (Base Station System), which are connected to the Control Centres, hereinafter referred to with the abbreviation MSC (Mobile Services Switching Centre). The latter allow a connection both to other MSCs, therefore to other mobile phones, and to the fixed network.

The BSSs and MSCs are fixed units and can be connected using
15 optic fibre or with conventional electric cables.

Each BSS consists of a Controller, hereinafter referred to with the abbreviation BSC (Base Station Controller), connected to a plurality of transceivers, hereinafter referred to with the abbreviation BTS (Base Transceiver Station), which basically form the terminals of the fixed part of the network which controls communication between mobile phones.

In order to improve the quality of the signal and cover the widest possible areas, the BTSs are placed in strategic positions, in particular in high places, for example on the top of particularly tall buildings.

With the introduction of third generation (UMTS, Universal Mobile Telecommunications System) mobile phones, this is no longer possible, since the structure of the new base stations is much more bulky and heavy and, as a result, much more difficult to handle from a logistics viewpoint. It is easy to imagine how positioning it on a roof, for example, could be extremely problematic.

Therefore, a slight variation of the conventional structure of the BSSs became necessary, disconnecting the BTSs from the antennas and inserting interface units to control the communications traffic between the BTSs and the remote units (RU -
 5 the terminals which comprise the antennas for sending/receiving radio frequency signals to/from mobile phones).

The second section of the connection between the BTSs and RUs, from the interface to the RUs, is normally created using optic fibre with significant advantages in terms of the quality of the
 10 communication (low attenuation) and the speed of data transmission.

The data exchange between BTSs and RUs must occur in both directions. The data from the BTSs to the RUs and, as a result, to the mobile phones, is the Down-Link (DL), whilst the signals from
 15 the mobile phones received by the RUs and sent on to the BTSs are the Up-Link (UL).

Two different wavelengths are normally used for the above-mentioned data exchange, one for the DL and one for the UL.

A typical example of the connection between the base stations and remote units is the so-called "backbone" configuration. An
 20 optic fibre cable runs from the interface unit to all of the RUs and ends close to the last RU. Each RU picks up a portion of the signal present in the fibre, selects the DL wavelength, transforms the optical signal into an RF signal and sends it to the mobile
 25 phone by means of an antenna. In parallel, if the RU must send data to the BTS, it sends a UL signal at a preset wavelength, different to that of the DL, in the optic fibre.

In this way, there are two data flows supported by the optic fibre, one from the interface unit to the RUs (DL) and one, in the
 30 opposite direction to the first, from the RUs to the interface unit (UL).

The UL and DL can be provided using two physically different supports (one fibre for the DL and another fibre for the UL), without significantly altering the structure and operation of the
 35 above-mentioned configuration.

The main disadvantage of this type of connection between the BTSs and RUs is the excessive waste of band in order to set up a

The network 1 basically consists of an operator 2 (a unit controlled by a telecom company, which allows connection to the rest of the telephone network, both mobile and fixed) and a first remote unit 3 and at least a second remote unit 4, which use antennas and suitable circuit equipment to allow signals to be exchanged between the operator 2 and the mobile terminals 5. Between the operator 2 and the remote units 3, 4 there is an interface unit 6, designed to control the data traffic between the operator 2 and the remote units 3, 4.

The network 1 may comprise two or more operators, that is to say, a plurality of blocks controlled by different telephone companies for connection to the rest of the telephone network. In this case, the interface unit 6 controls access to the remote units 3, 4 depending on the requirements of each operator.

Advantageously, each operator 2 communicates with the interface unit 6 by transmission and reception using two carriers, each having a separate physical support.

The interface unit 6 is connected to the remote units 3, 4 using a first transmission support 9, preferably consisting of optic fibre, with at least a first end 10 connected to an interface unit 6 input 7, and at least a second end 11 connected to an interface unit 6 output 8. In this way, the remote units 3, 4 can send/receive signals to/from the interface unit 6 and, as a result, a bi-directional data flow is possible between the remote units 3, 4 and the operator 2.

As illustrated in Figure 1, the interface unit 6 consists of a signal transmission circuit 25 and a signal reception circuit 26.

The signal transmission circuit 25 is positioned at the interface unit 6 output 8 and is connected to the second end 11 of the first transmission support 9. It is basically designed to pick up the signals from the operator 2 and send them to the remote units 3, 4 using the first transmission support 9. The signal transmission circuit 25 is made with a first routing matrix 27, a first electro-optical converter unit 28 and a multiplexer 29. The first routing matrix 27 has at least one input connected to the operator 2 and a plurality of outputs, each connected to a remote unit. The first routing matrix 27 is designed to route the signals

from the operator 2 to the remote units 3, 4 pre-selected by the operator 2.

The electrical signals at the first routing matrix 27 outputs are converted into optical signals by the first electro-optical converter unit 28, so that they can then be sent using an optic fibre support. Finally, the multiplexer 29 downstream of the converters 28, bundles and transfers all optical signals in a single physical support, that is to say, the first transmission support 9.

Therefore, inside the first transmission support 9, a main signal 44 is transmitted, containing all of the data to be sent from the operator 2 to the remote units 3, 4 and vice versa, the data to be sent from the remote units 3, 4 to the operator 2.

Figure 3 shows how the main signal 44, propagating in the first transmission support 9, consists of a plurality of secondary signals 45 identified by a preset parameter value characteristic of the main signal 44. Advantageously, said parameter may be the wavelength and each secondary signal 45 is, therefore, identified by its own wavelength λ_i , λ_{i+1} , λ_{i+2} , etc.

Conveniently, to optimise use of the optic fibre, that is to say, to maximise the number of carriers supported by the fibre, the wave division multiplexing (WDM) technique is used, which consists in sending data along the same fibre, using two or more signals with different wavelengths.

In particular, dense wave division multiplexing (D-WDM) is used, fixing the separation of the signal wavelengths propagating in the optic fibre in the 0.5 - 5 nm range.

Advantageously, semi-dense wave division multiplexing (SD-WDM) can also be used, in which special lasers modulate the signals, which are propagated at the third window of the optic fibre (propagation in an optic fibre occurs in three wavelength ranges, called "windows", the third corresponding to wavelengths of around 1550 nm).

The signal reception circuit 26 is completely symmetrical relative to the signal transmission circuit 25 described above. It has a demultiplexer 30, connected to the first end 10 of the first transmission support 9, to separate the various secondary signals

45 from the remote units 3, 4 sent to the circuits downstream by means of a plurality of outputs. The optical signals from the demultiplexer 30 are then converted into electrical signals by a second electro-optical converter unit 31, then sent to the operator 2 (or operators) by means of a second routing matrix 32.

In light of this, it is obvious how the interface unit 6 is able to control the traffic of signals between the operator 2 (or operators) and the remote units 3, 4.

Figure 2 is a block diagram of a single remote unit. It comprises a signal transmission block 12, connected to the first transmission support 9 to pick up at least one secondary signal 45a from the main signal 44 (the secondary signals 45 are then sent to the mobile terminals 5 by means of an antenna 14) and a signal reception block 13, which receives the RF signals from the mobile terminals 5 by means of the antenna 14 and adds them to the main signal 44 in the first transmission support 9.

Conveniently, the signal transmission block 12 is made using an optical filter element 15 to pick up at least one secondary signal 45a from the main signal 44, a first electro-optical converter 17 to transform the secondary signal 45a into an electrical signal, a first amplifier block 18 and a first RF filter 19 to treat the electrical signal before transmitting it in radio frequency to the mobile terminals 5 by means of the antenna 14.

Similarly, the signal reception block 13 comprises a second RF filter 20 and a second amplifier block 21 for treating the RF signals arriving from the mobile terminals 5 and received by the antenna 14, a second electro-optical converter 22 to transform the electrical signals into optical signals and a signal reception element 26 connected to the first transmission support 9 to add the contributions received from the mobile terminals 5 to the main signal 44.

Advantageously, to equalise the secondary signal 45a and prepare it for subsequent processing, the signal transmission block 12 has a first equaliser block 16 downstream of the optical filter element 15 and the signal reception block 13 has a second

creation of a communications network which is resilient and characterised by the high quality of the connection between the operators and the remote units.

The invention described can be subject to modifications and variations without thereby departing from the scope of the inventive concept. Moreover, all the details of the invention may be substituted by technically equivalent elements.